

# Rack Mounted Power Supplies

AC 24V  
DC 12V/24V/48V

**PATRIOT**  
POWER SUPPLIES  
BY PSS DISTRIBUTORS



## Features

- Compact 1RU power supply
- Fused input
- Illuminated input switch
- Individually fused outputs
- LED indicators on all outputs
- Battery back-up for 24V DC(option)
- Adjustable voltage for DC units
- Low battery signal (11 or 22V DC) for DC units
- Low voltage cut off (10 or 20V DC) for DC units



 N12754

## Specifications

Model	Description	Dimensions (HxWxD)
<b>24V AC</b>		
R-AC24-4A	1RU, 24V AC, 4 x 1A Outputs	45(1RU)x441x200mm
R-AC24-8A	1RU, 24V AC, 8 x 1A Outputs	45(1RU)x441x200mm
<b>12V DC</b>		
R-DC12-4A	1RU, 12V DC, 4 x 1A Outputs	45(1RU)x441x200mm
R-DC12-8A	1RU, 12V DC, 8 x 1A Outputs	45(1RU)x441x200mm
R-DC12-12A	1RU, 12V DC, 12 x 1A Outputs	45(1RU)x441x200mm
<b>24V DC</b>		
R-DC24-13A	1RU, 24V DC, 8 x 2A Outputs	45(1RU)x441x200mm
<b>48V DC</b>		
R-DC48-7A	1RU, 48V DC, 8 x 1A Outputs	45(1RU)x441x200mm
<b>13.5V DC with 1x 12V/7AH battery backed power supply 2RU (can hold 4 batteries)</b>		
RB-DC12-8A	2RU, 13.5V DC, 8 x 1A Outputs	90(2RU)x425x367mm
<b>27V DC with 2x 12V/7AH battery backed power supply 2RU (can hold 4 batteries)</b>		
RB-DC12-4A	2RU, 27V DC, 4 x 1A Outputs	90(2RU)x425x367mm
<b>Power supply battery bank</b>		
BB4-9	Fits 4 x 12V 9AH, takes 1-2 internal charger	90(2RU)x425x367mm

Specifications subject to change without prior notice.